












## 2 Légende groupes cames standard

N. et type interrupteurs	N. et type cames	Code
1 x PRSL0455PI	1 came A	PRFC0101PE
2 x PRSL0003XX	2 cames A	PRFC0008PEC
	2 cames C	PRFC0009PEC
3 x PRSL0003XX	3 cames A	PRFC0004PEC
	3 cames C	PRFC0006PEC
4 x PRSL0003XX	4 cames A	PRFC0202PEC
	4 cames C	PRFC0198PEC

## 3 Légende cames standard

Came	Angle de commutation	Code
A  1 pointe	20,5° ±0,5°	PRSL7140PI
B  10 pointes	14,0° ±0,5°	PRSL7142PI
C  Secteur 60°	78,0° ±0,5°	PRSL7141PI
E  Secteur 180°	199,5° ±0,5°	PRSL7144PI
H  Secteur 335°	344,0° ±0,5°	PRSL7143PI

## Légende interrupteurs

Type interrupteur	Commande auxiliaire				Commande directe
	PRSL0003XX	PRSL0011XX	PRSL0017XX	PRSL0195XX	PRSL0455PI
Catégorie d'utilisation	AC 15 - B300	AC 15 - B300	AC 15 - C300	AC 15 - C300	AC 3
Connexions	Faston 6,3 mm	Borne avec vis serre-fils	Borne avec vis serre-fils	Faston 6,3 mm	Borne avec vis serre-fils
Contacts	1NO+1NC 	1NO+1NC 	1NO+1NC 	1NO+1NC 	2NC 